

Docket 80097JDL

## EDGE ENHANCEMENT OF GRAY LEVEL IMAGES

1990 1991 1992 1993 1994 1995 1996 1997 1998 1999 2000 2001 2002 2003 2004 2005 2006 2007 2008 2009 2010 2011 2012 2013 2014 2015 2016 2017 2018 2019 2020 2021 2022 2023 2024 2025 2026 2027 2028 2029 2030 2031 2032 2033 2034 2035 2036 2037 2038 2039 2040 2041 2042 2043 2044 2045 2046 2047 2048 2049 2050 2051 2052 2053 2054 2055 2056 2057 2058 2059 2060 2061 2062 2063 2064 2065 2066 2067 2068 2069 2070 2071 2072 2073 2074 2075 2076 2077 2078 2079 2080 2081 2082 2083 2084 2085 2086 2087 2088 2089 2090 2091 2092 2093 2094 2095 2096 2097 2098 2099 2100 2101 2102 2103 2104 2105 2106 2107 2108 2109 2110 2111 2112 2113 2114 2115 2116 2117 2118 2119 2120 2121 2122 2123 2124 2125 2126 2127 2128 2129 2130 2131 2132 2133 2134 2135 2136 2137 2138 2139 2140 2141 2142 2143 2144 2145 2146 2147 2148 2149 2150 2151 2152 2153 2154 2155 2156 2157 2158 2159 2160 2161 2162 2163 2164 2165 2166 2167 2168 2169 2170 2171 2172 2173 2174 2175 2176 2177 2178 2179 2180 2181 2182 2183 2184 2185 2186 2187 2188 2189 2190 2191 2192 2193 2194 2195 2196 2197 2198 2199 2200 2201 2202 2203 2204 2205 2206 2207 2208 2209 2210 2211 2212 2213 2214 2215 2216 2217 2218 2219 2220 2221 2222 2223 2224 2225 2226 2227 2228 2229 2230 2231 2232 2233 2234 2235 2236 2237 2238 2239 2240 2241 2242 2243 2244 2245 2246 2247 2248 2249 2250 2251 2252 2253 2254 2255 2256 2257 2258 2259 2260 2261 2262 2263 2264 2265 2266 2267 2268 2269 2270 2271 2272 2273 2274 2275 2276 2277 2278 2279 2280 2281 2282 2283 2284 2285 2286 2287 2288 2289 2290 2291 2292 2293 2294 2295 2296 2297 2298 2299 2300 2301 2302 2303 2304 2305 2306 2307 2308 2309 2310 2311 2312 2313 2314 2315 2316 2317 2318 2319 2320 2321 2322 2323 2324 2325 2326 2327 2328 2329 2330 2331 2332 2333 2334 2335 2336 2337 2338 2339 2340 2341 2342 2343 2344 2345 2346 2347 2348 2349 2350 2351 2352 2353 2354 2355 2356 2357 2358 2359 2360 2361 2362 2363 2364 2365 2366 2367 2368 2369 2370 2371 2372 2373 2374 2375 2376 2377 2378 2379 2380 2381 2382 2383 2384 2385 2386 2387 2388 2389 2390 2391 2392 2393 2394 2395 2396 2397 2398 2399 2400 2401 2402 2403 2404 2405 2406 2407 2408 2409 2410 2411 2412 2413 2414 2415 2416 2417 2418 2419 2420 2421 2422 2423 2424 2425 2426 2427 2428 2429 2430 2431 2432 2433 2434 2435 2436 2437 2438 2439 2440 2441 2442 2443 2444 2445 2446 2447 2448 2449 2450 2451 2452 2453 2454 2455 2456 2457 2458 2459 2460 2461 2462 2463 2464 2465 2466 2467 2468 2469 2470 2471 2472 2473 2474 2475 2476 2477 2478 2479 2480 2481 2482 2483 2484 2485 2486 2487 2488 2489 2490 2491 2492 2493 2494 2495 2496 2497 2498 2499 2500 2501 2502 2503 2504 2505 2506 2507 2508 2509 2510 2511 2512 2513 2514 2515 2516 2517 2518 2519 2520 2521 2522 2523 2524 2525 2526 2527 2528 2529 2530 2531 2532 2533 2534 2535 2536 2537 2538 2539 2540 2541 2542 2543 2544 2545 2546 2547 2548 2549 2550 2551 2552 2553 2554 2555 2556 2557 2558 2559 2560 2561 2562 2563 2564 2565 2566 2567 2568 2569 2570 2571 2572 2573 2574 2575 2576 2577 2578 2579 2580 2581 2582 2583 2584 2585 2586 2587 2588 2589 2590 2591 2592 2593 2594 2595 2596 2597 2598 2599 2600 2601 2602 2603 2604 2605 2606 2607 2608 2609 2610 2611 2612 2613 2614 2615 2616 2617 2618 2619 2620 2621 2622 2623 2624 2625 2626 2627 2628 2629 2630 2631 2632 2633 2634 2635 2636 2637 2638 2639 2640 2641 2642 2643 2644 2645 2646 2647 2648 2649 2650 2651 2652 2653 2654 2655 2656 2657 2658 2659 2660 2661 2662 2663 2664 2665 2666 2667 2668 2669 2670 2671 2672 2673 2674 2675 2676 2677 2678 2679 2680 2681 2682 2683 2684 2685 2686 2687 2688 2689 2690 2691 2692 2693 2694 2695 2696 2697 2698 2699 2700 2701 2702 2703 2704 2705 2706 2707 2708 2709 2710 2711 2712 2713 2714 2715 2716 2717 2718 2719 2720 2721 2722 2723 2724 2725 2726 2727 2728 2729 2730 2731 2732 2733 2734 2735 2736 2737 2738 2739 2740 2741 2742 2743 2744 2745 2746 2747 2748 2749 2750 2751 2752 2753 2754 2755 2756 2757 2758 2759 2760 2761 2762 2763 2764 2765 2766 2767 2768 2769 2770 2771 2772 2773 2774 2775 2776 2777 2778 2779 2780 2781 2782 2783 2784 2785 2786 2787 2788 2789 2790 2791 2792 2793 2794 2795 2796 2797 2798 2799 2800 2801 2802 2803 2804 2805 2806 2807 2

Date: 8/1/00

## EDGE ENHANCEMENT OF GRAY LEVEL IMAGES

### Cross-Reference to Related Applications

5 This application is related to the following applications filed on even date herewith:

1. U.S. Patent Application Serial No. \_\_\_\_\_ filed in the names of Yee S. Ng et al, and entitled EDGE ENHANCEMENT PROCESSOR AND METHOD WITH ADJUSTABLE STRENGTH OF GRAY LEVEL OUTPUT.
- 10 2. U.S. Patent Application Serial No. \_\_\_\_\_ filed in the names of Yee S. Ng et al, and entitled EDGE ENHANCEMENT PROCESSOR AND METHOD WITH ADJUSTABLE THRESHOLD SETTING.
3. U.S. Patent Application Serial No. \_\_\_\_\_ filed in the names of Hwai-Tzuu Tai et al, and entitled IMAGE RECORDING APPARATUS AND METHOD PROVIDING PERSONALIZED COLOR ENHANCEMENT.
- 15 4. U.S. Patent Application Serial No. \_\_\_\_\_ filed in the names of Hwai-Tzuu Tai, and entitled GRAY LEVEL HALFTONE PROCESSING.

### Background of the Invention

#### Field of the Invention

20 This invention relates in general to digital image processing and, more specifically, to a digital image processing system and method for enhancing the edge characteristics of printed or displayed images that are subject to a halftone screening operation. The processed image data may be reproduced on a display or printing system using gray level pixels that vary in size or density depending upon  
25 the medium.

### Description Relative to the Prior Art

Multiple level halftones using gray level pixels are known to improve image quality of pictorial images for lower resolution printers. Different types of  
30 halftones are known to improve the stability of the (EP) electrophotographic process (such as full-dot or mixed-dot halftones, see in this regard "Gray Level Printing Method With Embedded Non-Uniformity Correction Method Using a

Multi-bit LED Printhead," IS&T 47 Annual Conference Proceeding, p. 622-625; 1994; and U.S. Patent No. 5,956,157, the contents of which are incorporated herein by reference thereto) or to improve on the reproduction of detail (such as partial-dot halftone). Image segmentation methods are known to distinguish  
5 between the input of local image types so that one can select different halftone types used for different local input image types (such as using a lower screen frequency mixed-mode halftone for pictures and interior of large text in order to improve the EP stability and reduce density contouring, and using a higher screen frequency partial-dot for finer fonts and edges to improve fine line reproduction).  
10 Blending of various multiple level halftones in the boundary regions of image types (using fuzzy logic type of approach) is also known to reduce abrupt transition artifacts between segmented image regions, see in this regard U.S. Patent Nos. 5,200,831; 5,694,224; and 5,956,157. A proper usage of the segmentation methods can produce good EP stability for large area images and  
15 produce fine line details, but it does not produce an anti-aliasing effect for near-saturated text and graphics. Anti-aliasing methods such as GRET (Gray Enhanced Anti-aliasing Technology) are known to produce enhanced anti-aliased text/graphics for input saturated text/graphics using multiple level rendering, see in this regard U.S. Patent Nos. 5,450,531; 5,600,761; and 6,021,256. However,  
20 GRET is not very effective to do anti-aliasing for non-saturated text. The inventors have recognized that it would be desirable that the above methods can be merged to produce an anti-aliasing effect for saturated as well as for non-saturated text (even with a multiple color system), to reduce effects from input scanner induced moire (such as input moire caused by high frequency features on  
25 images) and still maintain long-term stability of the color electrophotographic process.

#### Summary of the Invention

In accordance with a first aspect of the invention there is provided a  
30 method for processing gray level image data comprising subjecting the gray level image data to halftone screen processing to form halftone processed screen image data; analyzing a current pixel of the halftone processed screen image data to a

test criterion to determine if the current pixel is a possible saturated color text image; and if the current pixel meets the criterion for being a pixel of a possible saturated color text image providing a gray level image enhanced processing modification of the current pixel for output to a printer or display; and if the  
5 current pixel does not meet the test criterion for being a pixel of a possible saturated color text image providing the current pixel gray level as processed by the halftone screen processing for output to a printer or display.

In accordance with a second aspect of the invention there is provided a method for processing gray level image data comprising subjecting first gray level  
10 image data to plural separate halftone screen processings to form plural separate halftone processed screen gray level image data; analyzing a current pixel of the first gray level image data for contrast index; in response to the analyzing generating blending coefficients for processing that current pixel; processing the plural separate halftone screen processed image data with the blending  
15 coefficients to blend halftone screen processed gray level image data of the same current pixel to form a blended halftone screen processed gray level current pixel; comparing the gray level of the blended halftone screen processed current pixel relative to a threshold criterion; and if the gray level of the blended halftone screen processed current pixel meets the threshold criterion providing a gray level  
20 image enhanced processing modification of the blended halftone screen processed gray level current pixel for output to a printer or display; and if the gray level of the blended halftone screen processed current pixel does not meet the threshold criterion providing the current pixel gray level as processed by the blended halftone screen processing for output to a printer or display.

In accordance with a third aspect of the invention there is provided a method for processing gray level image data comprising: subjecting first gray level image data to plural separate halftone screen processings to form plural separate halftone screen processed gray level image data; blending halftone screen processed gray level image data of the same current pixel to form a blended  
25 halftone screen processed gray level value current pixel; and if the blended halftone screen processed gray level value current pixel is substantially a maximum density pixel or is adjusted to be a substantially maximum density pixel  
30

subjecting the blended halftone screen processed gray level current pixel to a gray level image enhanced processing modification to reduce jaggedness in an image.

In accordance with a fourth aspect of the invention there is provided an apparatus for processing gray level image data comprising: first and second  
5 halftone screen processing devices that form plural separate halftone screen processed gray level image data; an input to each of said screen processing devices to input image data representing a current gray level pixel; a device for analyzing the current pixel for contrast index; a device responsive to the contrast index for generating blending coefficients; a blending operation processor that  
10 generates a blended halftone data output for the current pixel; an input at the blending operation processor for inputting respective outputs of the first and second halftone screen processing devices and the blending coefficients; a gray level image enhancement processing device connected to the output of the blending operation processor; a detector for examining the current pixel after  
15 operation by the blending processor and neighboring pixels thereof after operation of the blending processor and determining if the current pixel and such neighboring pixels represent a substantially binary image file and generating a signal relative to such determination; and a selector, responsive to the signal, that selects either the gray level image enhancement processing device output or a  
20 bypass representing a blended halftone data output.

The invention and its further objects and advantages will become more apparent after reading the detailed description of the preferred embodiments presented below.

#### 25 Brief Description of the Drawings

In the detailed description of the preferred embodiments of the invention presented below, reference is made to the accompanying drawings in which:

FIG. 1 is a schematic block diagram of an image processing system according to the invention;

30 FIG. 2 is an illustration of a window of nine pixels and illustrates one exemplary approach to determining contrast index;

FIG. 3 is a view illustrating a determination of a blended rendered dot value using a graph depicting blending coefficients vs. contrast index for each of two different halftone processings;

FIG. 4 is a block diagram showing greater detail of a portion of the system  
5 of FIG. 1;

FIG. 5 is another block diagram showing greater detail of a portion of the system of FIG 1;

FIGS. 6 (a), (b) and (c) are illustrations of 19 x 19 pixel halftone screen tiles that may be used as one of the halftone screens in the system of FIG. 1;

FIGS. 7 (a), (b) and (c) and 8 are illustrative examples of screen address  
10 "bricks" and lookup table respectively that are used to generate halftone screen pixel rendered values for the pictorial screen of FIGS. 6 (a), (b) and (c);

FIG. 9 is a flow chart that may be used to determine a brick coordinated address in a lookup table structure of FIG. 8;

FIG. 10 is an example of a text screen tile for use in determining a halftone  
15 rendered text screen value;

FIG. 11 is an example of the screen address brick that is used to generate the halftone screen pixel rendered values for the text screen of FIG. 10;

FIG 12 is a block diagram of a preferred gray level edge enhanced  
20 processor used in the system of FIG 1;

FIG. 13 is a chart illustrating a relationship relative to different types of output from the gray level edge enhancement processor;

FIG. 14 illustrates schematically a binary image wherein 255 represents maximum density and zero represents background or no density;

FIG. 15 illustrates schematically a binary image that is provided with gray  
25 level edge enhancement in accordance with output from a medium strength setting for a lookup table;

FIG. 16 illustrates schematically a binary image that is provided with gray  
30 level edge enhancement in accordance with output from a low strength setting for a lookup table;

FIG. 17 illustrates schematically a binary image that is provided with gray level edge enhancement in accordance with output from a high-strength setting for a lookup table;

FIG. 18 is a graph showing a relationship of input pixel gray values to modified gray values in accordance with color saturation tweaking;

FIG. 19 is a block diagram of a printing or display system that incorporates the image processing system of FIG 1; and

FIGS. 20 (a) and (b) illustrate an example respectively of gray component replacement (GCR) and undercolor removal (UCR) in a color transformation process.

FIGS. 21-1 to 21-6 represent an illustration of steps for forming a brick structure;

FIG. 22 is a flow chart of a process for forming a brick structure;

FIGS. 23 (a)-(c) are illustrations of a tile structure and respective brick structures for a screen having 171 lines per inch at 0 degrees rotation angle; and

FIG. 24 is an illustration of a dot size driver having a circular or spiral type of growth pattern and used in generating rendered screen values for a tile.

#### Detailed Description of the Preferred Embodiments

The method described herein is intended for a full process color system that has multiple color separations, however the invention described is also applicable to black and white and accent color systems . There is herein described, for clarity purposes, a method and apparatus for processing image data for only one of the color separations of a plural process color separation image forming system. Extension to all color separations is an obvious matter such as by providing additional or parallel systems for each color or processing different colors serially. The input image to the system is assumed to be a continuous-tone color separation (post-RIP rasterized image) after GCR (Gray Component Replacement) and UCR (Under Color Removal) processings have already been applied. The input image data is gray level image data that may have been derived from scanning of a document by a scanner. In FIG. 1, there is shown a schematic of an image processing system according to the invention. A 1-D (one

dimensional) look-up table (LUT) 12 or global color process control (re-programmable) is used to operate on the input data so as to enable last-minute customer desired personalization or preference to affect the color separation coloring of the already rasterized image (such as redder, greener, etc.) during the

5 real-time running of the printing system. The modified input data as output by the LUT 12 is then input to and analyzed by an adaptive screen analyzer unit 14 (image segmentation) to generate an image type identification function (in this case, contrast index). This contrast index acts as a pointer to obtain blending coefficients (BC 1, BC 2) for the halftone screens of choice. In this example, it is

10 assumed that there are only two screens being used simultaneously (the text screen and a pictorial screen). It is understood that more intermediate screens can be used see in this regard U.S. patent No. 5,956,157 the contents of which are incorporated herein by reference . In this example contrast index is one known method of using the basic concept of image segmentation and fuzzy logic

15 approach to assign the percentage of usage of certain screens of choice.

The modified input contone data is also passed to the two screener or LUTs 18, 20 for halftone processing at the same time. In each of the screener LUT blocks, it is assumed that the input contone data is halftoned by only that screener (such as a very high frequency soft screen for text) under the control of a

20 screening address calculator 22 that has input from the pixel clock and line clock. A halftone rendered value is the output from each of the screening blocks 18, 20. In the case of rational screens, the repeating calculated address of the halftone blocks for the two screen choices are not necessarily the same. Then a blending operation is done in processor 24 that takes the blending coefficients and the

25 halftone values of all the screens into consideration so a blended rendered halftone value (blended halftoned value) based on the result comes out. Since the edges of non-saturated text/graphics have a high likelihood to use mostly the high frequency soft pictorial screen (which employs a partial-dot the growth pattern) and while the interior of the larger text has a higher likelihood to use mostly the

30 lower frequency (mixed-dot growth pattern) screen, fine details are preserved and the large area EP stability is achieved at the same time. Moreover, since the edges of non-saturated text are using higher frequency screens, it does not get degraded



by normal lower frequency screen processing (it is almost like an anti-aliasing effect is done for non-saturated text and graphics). The blending of screens also reduces the artifacts at the boundary of image types. This also reduces the moire problem caused by scanning input images that have high frequency features and output with a fixed screen (screen angle, screen frequency) halftone screens.

As noted in U.S. Patent No. 5,694,224 in gray level printing, each pixel has the capability to be rendered in several different dot sizes or densities, and thus different gray levels. The number of gray levels is at least three whereas in a binary system only two levels are possible, background and highest density.

However instead of simply providing each pixel with an independent gray level, several pixels may be organized together to form a super pixel, or cell. Each of the pixels in a cell is then provided with a gray level. The human visual response integrates the various gray levels of the individual pixels in the cell to a single perceived gray level for the cell. This is similar to the basic concept of binary halftoning. The number of tone skills for a cell is increased greatly, however, due to the number of different gray levels available for each pixel. For example, instead of only the two levels provided in binary halftoning for each pixel, 256 levels (including zero) can be provided with gray level printing for each pixel in the cell. The formation of the dots in the pixels of the cell can be performed in a number of different manners to achieve different desired results. The dots can be formed as "full" dot, "partial" dot, "mixed" dot or fixed dot to provide gray level halftoning. The partial dot formation process and mixed dot formation process are described in the aforementioned U.S. Patent No. 5,694,224.

Up to this point, the system can produce an anti-aliasing effect for non-saturated text and reduce moire caused by beating of the output screen to an input, and at the same time maintain stability for the EP process. The system also needs to produce an anti-aliasing effect for saturated text. Further, for color systems, since GCR and UCR are often used; some of the originally saturated text (in monochrome) has been changed to near-saturated text. In order to resolve this problem, a programmable adjustable threshold/detector 26 is used on the blended halftoned data (see FIG. 1). Thus blended gray level halftone values beyond a certain threshold are each converted , by GRET adjustable threshold/detector 26,

into a binary 1 value and the rest are set to a binary 0 value before they are input to the GRET anti-aliasing detector 28. In this regard reference is made to U.S. Patent Nos. 5,450,531 and 5,600,761 the contents of which are incorporated herein by reference for disclosure of GRET processing although other gray level edge enhancement processors may be used for improving edges of saturated text. Anti-aliasing edge enhancement output suggestions from GRET set the pointers to an LUT that contains multiple level output values to smooth the edges. Different strength (gray values) LUTs can be provided for the purpose of providing more or less smoothing or line-width control as shown in FIG. 1. This particular GRET strength selection being made by an input to LUT 30. Of course, based on the GRET algorithm for multiple level images, the detector 26 would also determine whether there are other values than the binary (a high but not saturated value and/or a low value) that exists within the window of examination. If there are other gray values within that window, the bypass gray values (blended halftoned values as output by blending operation processor 24) will be used instead. In this regard it will be noted that the GRET adjustable threshold/detector 26 provides additionally a bypass of the GRET processor 28 of the output of the blending operation processor 24. In addition to the bypass data a selector signal is provided as an input to the GRET or bypass selection device 32 so that the selection device 32 can determine whether to pass the GRET processed data as modified by GRET strength selector 30 or the bypass data which represents the blended halftoned data output by blending operation processor 24. There is thus accomplished anti-aliasing for near-saturated text/graphics in addition to the improvement in quality for non-saturated text as well in the method and apparatus of the invention.

In FIG. 2 there is illustrated a method to calculate the contrast index (that is the method used by the adaptive screen analyzer 14). In this method a window of nine pixels (which is taken from the output of global color process control device 12) is used and the absolute value differences between certain neighboring pixels are examined to determine a maximum difference between a pair of neighboring pixels. In this regard reference may be made to U.S. Patent No. 5,956,157.

In FIG. 3, there is shown an example of how the blending coefficients (BC 1, BC 2) are calculated (100 percent equal 1) in a two screener fuzzy logic system with the contrast index. There is also indicated an example of how the blended halftone value (rendered value) is calculated from the blending coefficients and  
5 halftone dot gray values of different halftone screen look-up tables outputs.

The current system offers independent tuning of the multi-level outputs within the LUTs from the two halftone screens and the GRET LUT edge values. It is desirable to match the two halftone screens gray levels and screen structure. In this regard there is provided a match of density and structure at the boundary  
10 region between image types, so the gray values within the two screener LUTs are tuned to achieve this match namely, at a similar input value, the output densities (not necessarily the same gray output values, since the screens are different) of the two screens are selected to match well (of course the screen structures of the two screens are also selected to reduce texture mismatch), so that a gradual transition  
15 between image type regions can be accomplished. For a similar reason, the gray values and GRET LUTs (high/medium/low-the high, medium, low refers to different degrees of aggressiveness in terms of anti-aliasing) are tuned independently from the screener LUT values in order to give an optimized performance for near-saturated text anti-aliasing effect (depending upon customer  
20 choice). The current system described herein provides the independent means for all of that to be done.

#### Preference Color Saturation Tweaking

~~A 1D (one dimensional) global color process control LUT 12 is used at the~~  
25 beginning to ensure the possibility of last-minute tuning of preference color even during the running of the printer after the images have already been RIPed (raster image processed). One input to LUT 12 is the 8 bit input data for the color separation image. The second input to LUT 12 is a color tweaking value for adjusting saturation of the color separation image. As shown in FIG. 18 there is  
30 provided a schematic illustrating the gray level input into LUT 12 and the corresponding gray level output from LUT 12 and the range of adjustments possible by modifying the color saturation on the output by the operator providing

5 a color tweaking adjustment input that is available at the control panel of the  
workstation WS in FIG. 19. It will be noted that this input comes after the job  
image buffer and is effectively modifying image data after the image data is  
output from the job image buffer. Thus experimentation may be done by the  
operator in making copies (such as proof copies) with various tweaking  
adjustments without rescanning of original hardcopy documents or rasterizing of  
the image data when the data is presented in electronic form. Preference color  
tweaking provides the last step of minor color adjustment to allow a user to adjust  
color if the user doesn't like the color being printed as may be observed from a  
proof print. Thus a de-saturated color may be adjusted back to a more saturated  
color. There may be provided the boosting of a specific color in the image. The  
coloring is not intended to provide fine-tuning of each color to be color accurate  
or to match color as a known color management process may be provided in a  
front end portion of the machine prior to rasterization. For full color or process  
color processes (cyan, magenta, yellow and optionally black) color tweaking is  
preferably performed before halftone processing because there are improved  
results obtained by modifying the contone (continuous tone) data rather than the  
halftone processed data. An advantage of having adjustments be provided to the  
contone data is that modifications to a dot structure or dot data formed after a  
halftone process may introduce unwanted artifacts (interaction from other color  
channels) in the dot structure and tends to provide more color variations or at least  
tends to be more difficult to predict/control adjustment of color.

In order to handle some limited degree of GCR/UCR ranges, an adjustable  
GRET threshold step is also provided at threshold detector 26 for different degrees  
of near-saturated text and graphics anti-aliasing needs. Other enhancements  
include putting more than one of the pictorial screens within the screener 2  
(screener 20) LUTs so different pictorial screens can be selected within one  
printed page without a need to reload the LUT (of course the screen address  
calculator's screen positioning increment calculation would need to be changed  
from one pictorial screen to the other). Further improvements include using more  
than two screens at a time in the blending operations for smoother transitions.

In FIG. 4, there is shown a detailed implementation of the functions such as the adaptive screen analyzer 14 (that generates the contrast index, please see FIG. 2 for its functional description), the blending coefficients LUT 16 (please see FIG. 3 for its functional description), and the detail of the blending operations block 24 (that utilizes the output values from the screeners and the blending coefficients as pointers to obtain an output value). In this case there is described a pre-calculated LUT approach (to obtain very high-speed operation) to generate the output (blended halftone data, please see FIG. 3 for the equations) to the GRET blocks (see FIG. 1 for detail). As may be seen in FIG. 3 after the contrast index is calculated the blending coefficients are generated according to the illustration in FIG. 3. For the example of a contrast index of 0.4 an output value from screener No. 1 (18) is multiplied by 70 percent while the output from screener No. 2 (20) is multiplied by 30 percent. As can be discerned from FIG. 3 contrast indices that are relatively small or relatively large have 100 percent multiplied by one screener value and 0 percent multiplied by another screener value.

In FIG. 5, there is shown a detailed implementation of the functions such as screen address calculator 22, screeners 18, 20 using LUTs (for high-speed operation) and the blending operation blocks 24 (blenders). To achieve higher speed, a dual processing channel approach is used. In this dual channel approach the current even pixel and the current odd pixel are separately simultaneously processed. In order to calculate contrast index of the current even pixel there is only required certain neighboring odd pixels of the current even pixel. For the current even pixel a first in first out buffer (FIFO) 21a is provided to store the neighboring odd pixels necessary for the contrast index determination for the current even pixel. Similarly, for the current odd pixel a FIFO 21b is provided to store the neighboring even pixels necessary for the contrast index determination for the current odd pixel. The current even pixels are input respectively to the even pixel screen LUTs 18a, 20a; and the current odd pixels are input respectively to the odd pixel screen LUTs 18b, 20b. The outputs of the screeners and the blending coefficients calculated from the respective contrast index for each of the odd and even pixels are input to the respective pixel blending operation processor 24a, 24b. For rational screens, coordinate addresses of rendered screen values

(depending on screen angles and screen frequency, different color separations can use different screener angles and frequencies, those addresses can be different) are generated in accordance with the description provided below. The pixel clock and line clock are used to increment counters depending upon the current pixel  
5 location with respect to the rational screens to obtain a coordinate output to the halftone screener LUTs (18a, 18 b, 20a, 20 b) that store the halftone screen multi-level output based on the input pixel value and coordinate value calculated.

#### Generation of Rendered Screen Values

10 With reference now to FIG. 6 (a), (b), (c) there is illustrated in each drawing a conventional screen tile defined within a 19 x 19 rectangular array. The screen tile is a 4 x 15 rotated square. The screen tile is used to render 154.6 LPI (lines per inch) screen rulings at 600 dpi (dots per inch) within 14.93 degrees screener angles. It will be understood that in each drawing the tile represents  
15 halftone rendering values for one gray value, 255, 128, 2 in an 8-bits per pixel system.

Reference will now made to the data in FIGS. 7(a), (b), (c) which illustrates for each of gray level planes 255, 128, and 2, a string of 241 numbers that can serve as a repeatable numerical series that represents the respective  
20 halftone tile. Although in FIG. 7(a) there are shown 241 numbers in various rows and columns, the 241 numbers are best visualized as being in a single row or brick of 241 numbers. For the case of planes 128 and 2 it is more apparent that in the typical gray level case the numbers in the brick are not all the same. As indicated in FIG. 7 (a), the brick width is 241, the brick height is 1, and there is an  
25 identification of a brick offset of 177, which will be described below. The use of the brick concept will be demonstrated to show that halftone rendering values may be determined for any pixel location in an image using the 241 values associated with each gray level. It will be understood of course that these 241 values are determined based on the screen ruling frequency, screen angle and size of screen  
30 tile and represent the halftone rendering values for only one color separation. Typically, it is desirable that each color separation have a screen angle different

from that of another color separation color when used to make the same multicolor image particularly with regard to pictorial halftone screens.

With reference now to FIG. 8 there is shown an illustration which is in furtherance of the explanation of the concept of the use of the brick series of numbers of rendering values. As shown in FIG. 8 a pixel value  $P(x,y)$  is input to an optional lookup table which is used in the situation where the incoming pixel is a different order (bit depth) from that of the rendering values. Thus, if the incoming pixel has a gray level bit depth of, for example, 12, it may be converted by the lookup table to a bit depth of 8. The pixel to be halftone rendered and modified so as to be of the appropriate bit depth is indicated as  $g(x,y)$ . The gray level of this incoming pixel identifies or serves as a pointer to one of 256 brick planes 0-255. Each brick plane incorporates the series of numbers of the brick for that gray level. Thus, plane 255 incorporates the series of 241 numbers shown in FIG. 7 (a). In addition to the gray value of pixel  $g(x,y)$ , there is also provided the  $x,y$  coordinate location or image pixel address for the pixel in the image. The coordinate location will be used to locate the specific rendering value for that pixel in the pixel plane defined by the gray level for that pixel.

Reference will now be made to the flowchart of FIG. 9 for calculation of a coordinate value  $I,J$  in a brick plane wherein there is known the current pixel's coordinate value in the  $x,y$  image plane. In the example provided the coordinate value  $J$  is at all times equal to one since in this particular case the brick height is one because of the nature of the halftone screen lines. For other screens the brick height may be two or more.

In order to determine a rendering value for the pixel  $g(x,y)$  the gray level plane is determined by the gray value of the pixel and consider now the first line of pixels to be rendered. The coordinates in the image plane of the first pixel in the first line of pixels are  $X=0, Y=0$ . The first number in the brick ( $I=0,J=0$ ) of the gray level plane of that pixel is the rendering value for this pixel. The second pixel in the first line of the image plane ( $X=1,Y=0$ ) is rendered by the second number in the brick of the brick plane having the gray level for that second pixel and so on for the first line of pixels  $g(x,0)$  until the 242nd pixel is to be rendered. For this pixel we return to the beginning of the brick string or series of numbers

and repeat from brick coordinate  $I=0$  to 240 in repeat fashion and so on until all pixels for line  $Y=0$  are halftone rendered.

For the next pixel line  $Y=1$  the first pixel in this line  $g(0,1)$  will map to offset location  $I=177$  in the brick, which location is particular for this screen, and  
5 different lines of the image will be found to have the starting position in the brick begin at different calculated offset locations. The next pixel in the image line  $g(1,1)$  will map to rendering location  $I=178$  and so on until location 240 is reached. Mapping of the next pixel in this image line then begins at rendering location  $I=1$ . Thus, an offset is only used to start a new image line at various  
10 calculated offset locations. Thus, for pixels in the second image line,  $Y=1$ , the pattern is a mapping sequence of  $I=177$  to 240 (for image pixels  $X=0$  to 63),  $I=0$  to 240 (for image pixels  $X=64$  to 304),  $I=0$  to 240 (for image pixels 305 to 545), etc. until all pixels in this line are halftone rendered. For the next following line  $Y=2$  the repetition pattern is  $I=113$  to 240, 0 to 240, 0 to 240, etc., until all pixels  
15 in this line are halftone rendered. It should be noted that for each pixel to be rendered a variable will be its gray level value so that a different brick plane is considered on a pixel by pixel basis depending upon the gray value of the pixel.

A robust implementation of this processing is indicated by the flowchart of FIG. 9 where the pixel having coordinates  $(x,y)$  is mapped to a certain location  
20  $(I,J)$  in a brick plane which location is then provided as one input to a halftone screen lookup table that also has input to it the gray value  $g(x,y)$  of the pixel. The lookup table stores rendered pixel values for halftone rendering of the image pixel  $g(x,y)$ . In this example there are  $241 \times 255$  rendering values in the LUT (brick width times number of brick planes). Further reduction of the size of the table can  
25 be made by recognizing that gray value 0 and 255 have  $I$  and  $J$  values that are irrelevant since in this example each pixel having a gray value of 0 and 255 is rendered at that respective value. In the flowchart of FIG. 9 the pixel image coordinate value  $x,y$  is input to a calculator that takes the value of the  $x$ -coordinate and adds that to a value of the  $y$  coordinate which has been first divided by the  
30 brick height and then multiplied by a brick offset value. This sum is then divided by the brick width wherein only the remainder is retained as the brick coordinate value for  $I$ . For example, where  $X=178, Y=1, Bh=1, Bs=177,$  and  $Bw=241$ , the



calculation is made of adding  $178 + (1/1)177=355$ , which is then divided by the brick width of 241 to yield a remainder  $I=114$ . The J coordinate value is determined by taking the y coordinate value in the image plane and dividing it by the brick height and retaining the remainder as the value for J. In this example for  
5 this screen the value of J is always zero, however, as noted above, some screens may have a brick height of two or more and so the J coordinate in the brick plane becomes essential to determine. Implementation of the brick coordinate calculator may be by software as processed by a computer or by a chip that is designed to perform this calculation. The calculation may be expressed by the formula:

10 
$$I = (X + (Y/Bh) * Bs) \%Bw$$

wherein “%” indicates that a division operation is made wherein a remainder is determined. As noted above, Bh in certain situations is equal to one so the equation simplifies in such situation to:

$$I = (X + Y * Bs) \%Bw$$

15 As noted in FIG. 5 separate simultaneous processing may be made of the odd and even pixels and a hardware or software implementation may be provided to accommodate calculation of brick coordinate value simultaneously for the odd and even pixels. In addition, since there will be rendering with both a halftone pictorial screen and a halftone text screen, there may be simultaneous  
20 implementation of calculations of brick plane coordinates for the text screen as well as the pictorial screen. An example of a text screen is illustrated in FIG. 10 and a look up table featuring rendering values utilizing the planes of bricks technique for rendering pixels processed by the text screen is illustrated in FIG.  
11. As may be seen, the text screen is significantly simpler than the pictorial  
25 screen and does not require rotation between color separations as is the case for pictorial screens. However, the particular text screen featured does have two rows of bricks for each brick plane.

Description of a technique for generating a look up table of rendered halftone screen values will be made with reference to FIGS. 21 and the flow chart  
30 of FIG. 22. As will become apparent the steps in the flow chart of FIG. 22 correspond to respective figure numbers in FIGS. 21. In FIG. 21-1 there is illustrated with shading a tile structure for a screen example having 141 lines per

inch at 600 dots per inch, with a 45 degree screen angle. The pixels identified as C1 represent those pixels which belong to the same tile. It will be understood that the entire image plane will be comprised of similar tiles that intermesh. It will be also understood in this example that the pixels forming the tile form one cell or super cell and that tiles may be formed having plural cells or super cells within a tile structure. In the case where the tile has plural cells or super cells there may be duplicative sets of pixel sequence numbers within a tile.

~~The individual pixels of the tile of this example have a unique location relative to other pixels within the tile and can be identified in this example as pixels with sequence numbers 1 through 18. Generally the shape of the tile structure and number of pixels therein and orientation of the tile is a function of the screen frequency and screen angle. In FIG. 21-2 the individual pixels in the tile are identified by the sequence numbers 1 through 18. In FIG. 21-3 the image plane is filled up with the sequence numbers of the respective tiles. In FIGS. 21-4 and 21-5 there are illustrated results of a search to find repeating rectangular blocks of sequence numbers in the image plane. As can be seen a minimum repeating block or brick is found that has a brick width (Bw) of six sequence numbers and a brick height (Bh) of 3 sequence numbers. As can also be seen the second course of bricks starts from an offset position of 3 sequence numbers, and this is referred to as brick offset or Bs.~~

After determining the parameters of the brick width, brick height and brick offset, the values for the look up table of rendered values may be substituted for the sequence numbers of the pixels. For this particular screen the sequence numbers for the pixels are consistent for all tile gray level values 1-255 for an eight bits per pixel system. However, for each tile gray level value a particular sequence number in the tile will correspond to a particular rendered value. This is illustrated in FIG. 21-6 which shows that for gray level 2 value for the tile that the pixel having sequence number 1 has a rendered gray level value of 106 while all other pixels in the brick have a rendered gray value of 0. In the example of the tile having a gray level of 128 it can be seen that only a few pixels in a tile have rendered values of 0 whereas other pixels have rendered pixel values other than 0.

At tile gray level 255, in this example, all pixels in the tile have a rendered value of 255.

With reference now to FIGS. 23 (a)-(c) there is illustrated the tile structure for a different screen that represents a screen structure for a tile having four cells or super cells within the tile structure. This tile structure corresponds to a screen having 171 lines per inch at 0 degrees angle of rotation. As can be seen in FIG. 23 (a) the four cells have three different shapes. A brick structure for this tile is also illustrated in FIG. 23 (a). As can be seen this brick structure has the brick height of 7 with no brick offset. In FIGS. 23 (b) and (c) the brick structure and the tile structure are illustrated with respective rendered pixel values for tile gray levels 2 and 128 for a halftone dot having a distributed dot type growth pattern. In this type of halftone dot growth pattern of gray level dots in a cell, growth tends to be distributed to several pixel members of the cell as cell gray levels increase. This growth pattern is different from the full dot type growth pattern wherein growth of cell gray level tends to increase through increasing the gray level of one pixel until the pixel becomes a maximum gray level at which point gray level growth of the cell tends to increase at a next pixel location in the cell. It will also be noted that the brick structure corresponds to the tile structure in this example.

In order to generate rendered screen values for a tile the various tile parameters such as screen angle, lines per inch, number of gray levels per pixel are considered. In addition the nature of the dot driver and dot type growth pattern are also considered. An example of a dot driver is illustrated in FIG. 24 for a 16x16 dot size driver having a circular or spiral type of growth pattern wherein dots in a cell tend to grow from the center outwardly. Other types of dot drivers may be used and suited to other shapes of growth patterns such as growth along a line, or an ellipse. These factors may be input to a dot membership function generator which considers cells within a tile and the contribution of spill over exposure at a pixel location of exposures from other pixel locations from other cells forming a part of the tile. A screen profile builder may then be used to determine the total gray level in the tile by summing of the exposure values at pixel locations that are not yet quantized. A screen profile quantizer then quantizes the individual pixel rendered values so that these values can be

expressed in a form of a whole number, for example, 0-255 in a system having an eight bits per pixel bit depth.

It will be understood of course as described herein an assignment of a rendered screen value does not imply that this is a value that is output directly to a printer as other image processing operations may be implemented upon the rendered screen values obtained. Thus as described herein a rendered screen value for a particular pixel may be subjected to thresholding to establish eligibility for further processing such as edge enhancement processing or to a blending operation.

10 A functional block diagram of a one example of an edge enhancement processing system that may be used in the method and apparatus of the invention is illustrated in FIG. 12. As noted above, the input into the GRET processor 28 is in the form of a binary bitmap through adjustment by GRET adjustable threshold/detector 26. This is with regard to data that has been subject to  
15 thresholding. The data output by the blending operation processor 24 is also bypassed to the GRET or bypass selection device 32. The input into the GRET processor 28 is a binary bitmap where the term "binary" bitmap or image is understood by those skilled in the art to refer to a bitmap or image in which image pixels are either fully or substantially fully exposed or are unexposed or  
20 substantially unexposed, i.e., substantially no gray-scale pixel data is present. As the GRET processor, in this example, may process pixels at a bit depth of four bits per pixel, the detector 26 may modify the eight bits per pixel image data into the four bits per pixel bit depth required by the GRET processor. The term "gray-scale" refers to image data wherein each pixel is represented by more than one bit  
25 of data to indicate one or more shades of gray between fully exposed and fully unexposed. Of course, the actual color of the pixel will be dependent upon the color toner or pigment used in a printing process to develop the pixel. As an example where image data is represented by four binary bits of information, a binary bitmap will have image data represented by either 0 or 15. The binary  
30 bitmap includes rows and columns of this image data wherein 0 may represent an unexposed pixel and 15 may represent the pixel area being fully exposed. Of course, these can be reversed. Development is preferably at the exposed pixel

area and no development at the unexposed pixel area (known as discharged area development or reversal development but alternatively charged area development may be used). While reference herein is made to "exposed" and "unexposed" pixels, it will be understood that in other printing or display systems equivalent representation of pixels will be provided according to the nature of the system, even though the nature of the system does not employ an exposure, for example, inkjet which employs a deposit of ink.

In the GRET processor 28 the current pixel position as output from a band buffer 100 is indicated by the term  $n(i,j)$ . Sobel gradient masks 120,140 for both the horizontal and vertical directions operate on the binary bitmap data  $n(i,j)$  to produce a gradient x operator (gx) and a gradient y operator (gy). Typical sobel gradient masks that can be employed include those described in U.S. Patent No. 6,021,256, the contents of which are incorporated herein by reference. Other gradient masks may also be used. The gradient amplitude or magnitude (gm) is then calculated by a processor 160 by taking the square root of the sum of the square of the gradient x operator (gx) and the square of the gradient y operator (gy) for each location in the bitmap to produce a gradient magnitude map. The gradient magnitude map is then stored in a buffer 180 for later use. Similarly, the gradient angle (ga) 220 is determined for each pixel location to produce a gradient angle map 220. For purposes of convenience, the gradient angle (ga) is preferably limited to a choice of gradient directions (gd) by a gradient directions sorter 240. The gradient direction for each location is stored in a buffer 260. The original bitmap data and the gradient magnitude (gm) and gradient direction (gd) corresponding thereto are supplied to a decision matrix 280, which uses this information to select edge enhanced gray-scale output data to replace the binary bitmap data entering the GRET processor. The decision matrix 280 determines whether the central pixel of a window of the binary bitmap data is a black or white pixel, whether the central pixel is contained in a single pixel line and the position of the pixel with respect to a kink site, by comparing the pixel data to a set of criteria represented by predetermined pixel values and gradient magnitudes. In accordance with rules establishing a set of criteria, the decision matrix 280 generates an address that is supplied to a look-up table LUT 30. The LUT 30

generates edge enhanced gray-scale output data based on the address generated by the decision matrix 280. The enhanced gray scale output data replaces the binary input data output by the threshold/detector 26 and produces a smoother image without jagged edges when applied to a gray scale printhead (for example, a laser, LED, thermal, inkjet or other type of printhead) of a printer or to a gray level display such as a CRT or other suitable display. It will be understood that the GRET system can be implemented as a computer program executed on a general-purpose computer or a dedicated programmed computer or in hardware as a pipeline processing system, particularly in the form of an application-specific integrated circuit (ASIC), or a combination thereof. The LUT 30 as noted in FIG. 1 may be a series of high/medium/low LUTs 30 each of which may be selected by input of a GRET strength selector signal to provide preferences for the type of or strength of edge enhancement.

#### 15 Variable Strength GRET

With reference now to FIGS. 13 and 14-17 there will now be provided a description of the operation of the variable strengthening of the GRET output. In FIG. 14 there is illustrated an original image that is binary and represented by eight bits per pixel so that the value 255 represents pixel areas where there will be maximum development while pixel areas indicated as 0 represents no development or background. The image represents various lines emanating from an origin location that run at different angles relative to the origin. It will be noted that there is a staircasing effect or jaggedness in certain of these radiating lines, and it is an object of this resolution enhancement device to attempt to minimize this jaggedness by placement of gray level pixels at particular sites at the periphery of the lines to provide an appearance of relative smoothness. Consider now FIG. 15 wherein there is shown a GRET output wherein the lookup table 30 is adjusted for medium strength. In now comparing FIGS. 16 and 17 with that of FIG. 15, it will be noted that for cases of GRET output using a high-strength lookup table the gray level values added by the GRET processor are different for the cases of high-strength, medium strength and low strength. It will also be noted that values that are binary in nature; i.e., 0 or 255, are not affected. Thus, this

provides an additional adjustment to the operator at the workstation WS in allowing for personal preference input adjustments by the operator towards improvements in anti-aliasing. The operator merely selects which option of LUT 30 (high, medium, low strength) he/she prefers to improve on reduction in jaggedness.

#### Adjustable Threshold Input for GRET Processing

In FIG. 19 there is shown a printer or display apparatus 400 which includes the image processing system 10 described above. The apparatus includes a document that is scanned by a scanner 410 which generates an 8-bit signal representing density scanned. The raw scanned image data typically in the form of red, green, blue (R,G,B) may be buffered in a buffer 412 and is then subject to color and other image processing such as gamma correction 414. When the image data is in the form of one color system there is a need to convert the color image data to a different color system by a color transformation operation 416. The transformed color separation image data normally used with a printer is preferably C,Y,M,K. As noted above, the color transformation processor may be provided with under color removal and/or gray component replacement as is well known. The function of under color removal is mainly to reduce chromatic color (yellow, magenta and cyan) in the dark or near-neutral shadow areas in order to reduce toner height or toner coverage. Gray component replacement is similar but refers to use of black toner for the gray component of any color and is not restricted as is under color removal to the near-neutral color area. Although the purpose of these two techniques are different, in reality they are similar in terms of employing black toner to reduce some of the chromatic toners from the image. With reference now to FIGS. 20 (a) and (b), there is provided an example of GCR and UCR with a brown mixed color. The GCR function permits the gray component of the chromatic printing inks or toners to be replaced by black process color, with an effect in the entire color space. The amount replaced can be set as desired. The color impression remains the same. Less color is needed to create a specific hue, i.e., the area is reduced. This means that the gray axis is more stable. Since fewer chromatic colors are used, cost can be reduced. UCR is an additional or

optional setting option in chromatic reproduction. In this process, the gray component of the chromatic printing inks or toners is replaced by black in neutral image shadow. Less color is needed to create a specific hue, i.e., the area is reduced. This means that the gray axis is more stable and fewer chromatic colors are used, cost can be reduced with UCR as well. Although it is known to provide a UCR and/or GCR processor after color space transformation, it is more preferable to provide for it during the color space transformation. A problem associated with employing UCR and/or GCR is that the most saturated color values produced by the processing may not reach the levels that would otherwise indicate that they represent binary data image information. For example, the threshold/detector 26 is provided with a certain preprogrammed threshold level values above the threshold level assumed to be binary information. If certain color transformation processes are employed in which all the process information falls below this preprogrammed threshold level, then all the information will be assumed to be a non-binary image data file and will be subject to bypass of the GRET processor. The operator of the printer will be aware of the color transformation processes being employed and can therefore through adjustment of the threshold input to the GRET adjustable threshold/detector 26 provide for a new threshold level taking into account what will substantially be considered a useful threshold above which would indicate a binary image data file. For example, typically a binary image file might be represented by saturated color gray values in an 8-bit depth system wherein the gray values are considered to be 254 or 255. Thus, a threshold value of 253 might be established in the threshold/detector 26. However, particularly where UCR and/or GCR are employed, maximum gray values may be no more than 253. The indication would, thus, be that no binary image data file is present and selection would be made of only data that has bypassed the GRET processor. However, this result belies the nature of the image information because of the nature of the processing in the color transformation. In order to overcome this problem, the operator is provided an opportunity through a programmed adjustable threshold input to establish a new threshold for determining what is defined to be a binary image data file so that improved control is now provided between which image data will



be subject to selection either data that has bypassed the GRET processor or image data which is subject to GRET processing. Thus, for example, where UCR and/or GCR are employed the operator would establish a lower threshold than say 253 for the GRET threshold/detector 26 in order to be sure that some of the information selected for output would be that from the GRET processing. Alternatively, a lower threshold may be established by altering the threshold value automatically upon selection by the operator of under color removal and/or gray component replacement or an adjustment in the amount of under color removal and/or gray component replacement.

10       The raw scanned image data may be subject also to other corrections as is well known in the prior art. Input from an electronic data source 420 may also be provided of pages of image data that may also be input to a job image buffer 424 after rasterization by a raster image processor (RIP) 422. One or more pages of rasterized image data from the scanner or the electronic data source are stored in  
15       the job image buffer (JIB), preferably in compressed form, allowing collated sets of multipage documents to be printed by electronically recirculating the image data in the job image buffer after the data has been sent to the printer. In this regard reference may be had to U.S. Patent No. 5,047,955 filed in the name of Shope et al, the contents of which are incorporated herein by reference. The  
20       image data is output to an image processing system 10 described above for ultimate output to a gray level printhead or display 470. The printhead may be provided with correction by a writer interface board 460 for correcting for nonuniformities of the recording elements or other known correction devices or schemes such as those which adjust exposure level through pulse-width  
25       modulation, pulse intensity modulation, etc. In this regard reference is made to U.S. Patent No. 6,021,256, filed in the name of Ng et al, and U.S. Patent No. 5,914,744, filed in the name of Ng. Overall control of the apparatus may be provided by marking engine controller 426 that may be in the form of one or more microcomputers suitably programmed to provide the control in accordance with  
30       well-known programming skills. A workstation WS provides input to the marking engine controller of various job parameters relative to the printing job, such as number of copies, paper selection, etc., including the GRET adjustable threshold

input value used by the detector 26, GRET strength selection (high, medium, low LUT) and the real-time color tweaking adjustment used in LUT 12.

In the preferred apparatus of the invention the printhead of say 600 dpi resolution exposes a uniformly charged photoconductive drum or web and the web is developed with pigmented electrosopic toner particles to develop the image. The developed image, as well as developed images of other color separations, are then transferred either serially in separate operations or in one operation to a receiver sheet either directly from the photoconductive web or drum or indirectly via an intermediate transfer member and in this regard reference is made to U.S. Patent No. 6,075,965, issued in the name of Tombs et al, for description of a color electrophotographic machine for serially transferring color separation images to a receiver sheet.

Extension of this method includes storing more than one pictorial screen within one of the screeners, so different pictorial screens can be used within the printed page (or the next page without reloading the screener LUT). Of course, in this case one will need to store more than one set of screen addresses (in the Row and Column LUTs). Also a selector function at say the workstation WS of which pictorial screen to use will need to be included.

Other extensions on the subject include the usage of an irrational screen coordinate calculator (the errors for screen angle and frequency calculation can be propagated forward, so adjustment of subsequent screen blocks can be done to correct for those errors), such that irrational screens can be used and one can obtain more choices of accurate screen angles and frequencies using this method with a lower addressability output device. In more detail, the screen coordinate calculator calculates the LUT data addresses for each step through the screen brick, and accumulates a position error due to stepping through the brick. This position error is corrected by making address jumps when a pre-defined position error threshold is exceeded.

There has thus been described an improved apparatus and method wherein a gray level image data file which may contain pictorial or non-saturated text images and saturated text images and that these respective images may be

The invention has been described with reference to certain preferred embodiment thereof. It will be understood, however, and modifications and  
5 variations can be made within the scope of the appended claims.